

# Phonitor-Vergleichstabelle



		Phonitor xe	Phonitor x	Phonitor e	Phonitor se	Phonitor 2
Phonitor Matrix	Crossfeed	6 Werte	6 Werte	2 Werte	2 Werte	6 Werte
	Speaker Angle	22°/30°/40°/55°	22°/30°/40°/55°	30°	30°	15°/22°/30°/40°/55°/75°
	Center Level	○	○	○	○	●
	Matrix an/aus	●	●	●	●	●
Remote Control*	Volume	●	●	●	○	●
Laterality Control	Sehr feine Balance	●	●	○	○	●
Stereo/Mono	Wiedergabe-Modi	●	●	○	○	●
Mute	Stummschaltung	○	●	○	○	●
Solo L/R & Phase	Monitoring-Funktionen	○	○	○	○	●
VU Meters	Ø 36mm beleuchtete VUs	●	●	○	○	●
	0dB VU Kalibration	0 / 6 / 12 dB	0 / 10 dB	○	○	0 / 6 / 12 dB
Headphone Outputs	Ausgänge Vorne und hinten	●	○	○	○	○
	Zusätzlicher Ausgangspegel-Boost	+22 dB	+12 / +22 dB	+22 dB	+12 dB	+6 / +12 dB
	6,35mm (1/4") Stereroklinke	●	●	●	●	●
	Ausgangsleistung (1 kHz, 1 % THD, 600 Ω)	2 x 2,7 W	2 x 2,7 W	2 x 2,7 W	2 x 2,7 W	2 x 2,7 W
	Ausgangsleistung (1 kHz, 1 % THD, 250 Ω)	2 x 5 W	2 x 5 W	2 x 5 W	2 x 5 W	2 x 5 W
	Ausgangsleistung (1 kHz, 1 % THD, 32 Ω)	2 x 1 W	2 x 1 W	2 x 1 W	2 x 1 W	2 x 1 W
	4-pin XLR (symmetrisch)	●	●	●	○	○
	Ausgangsleistung (1 kHz, 1 % THD, 600 Ω)	2 x 8 W	2 x 8 W	○	○	○
	Ausgangsleistung (1 kHz, 1 % THD, 250 Ω)	2 x 3,5 W	2 x 3,5 W	○	○	○
	Ausgangsleistung (1 kHz, 1 % THD, 32 Ω)	2 x 0,7 W	2 x 0,7 W	○	○	○
Line-Ausgänge	XLR (symmetrisch, +4dBu)	○	●	○	○	●
	1/4" Jack (symmetrisch, +4dBu)	○	○	○	○	○
	RCA (unsymmetrisch, -10dBV)	○	●	○	○	○
	Lautsprecherausgang	○	●	○	○	●
Line-Eingänge	XLR (symmetrisch, +4dBu)	●	●	●	○	● (2x)
	1/4" Jack (symmetrisch, +4dBu)	○	○	○	○	○
	RCA (unsymmetrisch, -10dBV)	●	●	●	●	●
	RCA -10dBV to 0dBu Boost	●	○	●	○	●
DA-Wandler (optional)	Modell	DAC768	DAC768xs	DAC768xs	DAC768xs	○
	DLP120 (dual low pass filter)	●	○	○	○	○
	Bit/Max Abtastrate (kHz)	32/768	32/768	32/768	32/768	○
	DSD (max)	256 (11.2MHz)	256 (11.2MHz)	256 (11.2MHz)	256 (11.2MHz)	○
	USB	●	●	●	●	○
	AES	●	○	○	○	○
	Coaxial SP/DIF	●	●	●	●	○
Optisch SP/DIF (Toslink)	●	●	●	●	○	
Gehäuse	WxHxT (inkl. FüÙe)	278 x 100 x 330mm	278 x 100 x 330mm	278 x 100 x 330mm	278 x 100 x 330mm	278 x 100 x 330mm
		11" x 4" x 13"	11" x 4" x 13"	11" x 4" x 13"	11" x 4" x 13"	11" x 4" x 13"
	Gewicht	5,1kg/11.24lbs	4,3 kg/9.5 lbs	3,3kg; 7.3 lbs	3,1kg; 6.8 lbs	4,3kg; 9.5 lbs

\*Die Geräte lernen jede IR-Fernsteuerung. Sie ist nicht im Lieferumfang enthalten.